



The BaBar Online Detector Control System Upgrade


Stanford
Linear
Accelerator
Center



Matthias Wittgen, SLAC


Outline

- *BaBar Online Detector System*
- *EPICS*
- *Motivation for Upgrade*
- *First Attempt with RTEMS*
- *Second Attempt Linux*
- *Conclusions*





BaBar Detector Control System


- *17 IOCs in VME crates*
 - Mvme177 with 33Mhz 68040 and 32MB RAM
 - Commissioned in the late 1990
- *One infrastructure server*
 - Boot and disk server for IOCs
 - EPICS gateway
- *One application server*
 - Archiving, softIOCs
- *Two terminals for shifters*
- *Interconnected on private VLAN*
 - Security issue (access through gateway machines)



Detector Control System Setup



BaBar IOC overview



SVT: ~ 3400 channels

DCH: ~ 5000 channels

DRC: ~ 40000 channels

EMC: ~ 7000 channels



IFR: ~ 50000 channels

CEN: ~ 10000 channels




Experimental Physics and Industrial Control System

- *EPICS core application running on a I/O Controller*
- *Key concept is a database of records*
 - Values, Alarm Limits, Alarm Status
- *Records can refer to each other*
 - PV Replication, Calculations
- *Records can get their input from device drivers*
 - Interface to Hardware (mainly VME)
- *PV can be distributed via LAN*
 - Channel access (monitoring, archiving, GUIs)




EPICS software upgrade

- *BaBar was using EPICS release 3.13 since startup*
- *Beginning of 2005 update of all IOCs to 3.14*
- *Major improvement in 3.14 is portability*
- *OSI (operating system independent) layer*
- *So called softIOC*
 - *IOC running on Linux/Solaris hosts*
 - *No hardware access implemented in OSI layer*
- *Improved stability*
- *But more hardware resources needed*
- *Supports more embedded OS than vxWorks*
 - *RTEMS*




Why upgrade?

- *Mvme177 not really available any more*
 - \$7000 for latest version with 50MHz CPU and 128 MB RAM
- *LST upgrade adds 20000 additional channels*
- *Several bottlenecks*
 - Memory
 - CPU too slow to serve EPICS channels
 - 10 MBit network
 - VxWorks network resources (number of file descriptors)



Hardware upgrade

- *Mvme5500*
 - 1 GHz PowerPC 7455 (equivalent to G4)
 - 512 MB RAM upgradeable to 1 GByte
 - Two network interfaces 100/1000 GBit
- *Already used in EPICS community*
- *BSP for vxWorks and RTEMS available*
- *Cost about \$3000*
- *Using vxWorks would have required no license*
- *Latest version was not supported by EPICS*



First Attempt: RTEMS

➤ *Real-Time Embedded System*

➤ *Pros:*


- Board support package for mvme5500
- Already supported by EPICS

➤ *Cons:*

- No shell or loadable module support
- Limited debugging support: remote gdb


➤ *CEXP*

- VxWorks like shell with loadable module support and C like regular expression language





First (failed) Attempt: RTEMS

- *In 2005 the LST was partially installed with 7 out of 21 HV power supplies integrated into the control system*
- *CANBUS interface for communication between HV power supplies and IOC*
- *System worked reliably through BaBar Run 4*
- *Didn't work with all 21 HVPS*
 - *No memory management in RTEMS*
 - *No overcommitment of memory*
 - *Running out of memory during startup*




Let's go Linux




Second Attempt: Linux

- *Kernel patches for MVME5500 for 2.6 from Motorola*
 - Not quit up-to-date. Two subversions behind
- *Embedded Linux Development Kit ELDK available for PowerPC*
 - Gcc cross-compiler for i386 Linux
 - Small base distribution with native gcc and gdb
- *Not really real-time, but EPICS isn't really either*
- *Write(small) OSI layer for EPICS to access VME*
- *Fine with polling device drivers*
- *Native Linux drivers for interrupt driven devices*
 - How to propagate interrupts into user-space



Problems Linux did solve


- *Found many bugs in our EPICS device drivers*
 - EPICS application can be run in gdb
 - Dereferencing of NULL pointer don't cause SEGV on vxWorks and RTEMS
 - Core dumps allowed us to find some race conditions leading to crashes
- *EPICS can run in user-space*
- *No reboots required any more*
 - Restart of EPICS application sufficient
 - 30 second downtime to make changes to EPICS instead of 2-10 mins for a reboot



Top on Linux IOC

```
top - 17:13:46 up 10 days, 22:00, 1 user, load average: 0.35, 2.10, 1.78
Tasks: 431 total, 3 running, 428 sleeping, 0 stopped, 0 zombie
Cpu(s): 4.6% us, 2.3% sy, 0.0% ni, 92.5% id, 0.3% wa, 0.0% hi, 0.3% si
Mem: 514868k total, 199040k used, 315828k free, 0k buffers
Swap: 0k total, 0k used, 0k free, 96120k cached
```

PID	USER	PR	NI	VIRT	RES	SHR	S	%CPU	%MEM	TIME+	COMMAND
3969	babar	16	0	140m	80m	2792	S	1.6	16.0	734:59.91	ifr-mon.iocsh
3984	babar	16	0	140m	80m	2792	S	1.6	16.0	1956:58	ifr-mon.iocsh
4817	babar	16	0	2916	1424	944	R	1.0	0.3	0:00.66	top
4025	babar	15	0	140m	80m	2792	S	0.7	16.0	1355:50	ifr-mon.iocsh
3957	babar	15	0	140m	80m	2792	S	0.3	16.0	255:13.53	ifr-mon.iocsh
3972	babar	15	0	140m	80m	2792	S	0.3	16.0	14:21.00	ifr-mon.iocsh
3985	babar	15	0	140m	80m	2792	S	0.3	16.0	800:50.88	ifr-mon.iocsh
4206	babar	16	0	140m	80m	2792	S	0.3	16.0	61:35.03	ifr-mon.iocsh
4252	babar	16	0	140m	80m	2792	S	0.3	16.0	4:53.38	ifr-mon.iocsh
1	root	16	0	1632	592	520	S	0.0	0.1	1:14.00	init
2	root	34	19	0	0	0	S	0.0	0.0	0:00.00	ksoftirqd/0
3	root	RT	0	0	0	0	S	0.0	0.0	0:00.04	watchdog/0
4	root	10	-5	0	0	0	S	0.0	0.0	0:00.08	events/0
5	root	11	-5	0	0	0	S	0.0	0.0	0:00.01	khelper
6	root	10	-5	0	0	0	S	0.0	0.0	0:00.00	kthread
15	root	16	-5	0	0	0	S	0.0	0.0	0:00.00	kblockd/0
59	root	20	0	0	0	0	S	0.0	0.0	0:00.00	pdflush



Conclusions

- *5 out of 17 IOC replaced so far by mvme5500*
- *Switching to Linux provided a very stable environment for running EPICS*
- *Better debugging tools*
- *Made IOCs running vxWorks more stable*
- *Went from about 2 IOC crashes a week to virtually zero*
- *Pentium based SBC probably better choice*
 - *Runs Scientific Linux out of the box*



References

➤ *EPICS*

- <http://www.aps.anl.gov/epics>

➤ *RTEMS*

- <http://www.rtems.com>

➤ *CEXP/GeSYS*

- <http://www.slac.stanford.edu/comp/unix/package/rtems/doc>

➤ *Kernel Patches for MVME5500*

- <https://mcg.motorola.com/cfm/templates/linux.cfm?PageID=705>

➤ *ELDK*

- <http://www.denx.de/wiki/DULG/ELDK>

